


Product System



BetaOpto with Environmental Focus of no UV, low heat, long life time, the LED is perhaps an impact on architectural luminaries, entertainment lighting, and contour lighting. BetaOpto's sleek controller design offers highly efficient engineering aids in RGB and white lighting control, and easy installation with housing dim. 4.85" x 4.70" x 1.2". It can be mounted into a fixture and led out only an IR remote sensor.

Light control thru the wireless IR controller, employ a slim aluminum box, controls the color light from one compact IR remote controller. With push-button, the controller enhances the ambient comfort in P8 programming modes of solid light and full color changing, and features M6 light memory, speed/brightness adjustment, chase on/off and light pause. The most common white is provided upon one simple touch on keypad W.



Wall mount profile, a feature to be embedded as a part of architecture, it employs a 30mm thick aluminum profile that can be easily installed behind the wall structure and structured a subtle concealment.

External connector provides one easy connection to external devices, such as PLC terminal.

USB port allows user friendly access to the animation **Color Edit 1 RGB** software program.

Slim Size 123*120*30mm (L*W*H)
Easy M5 hole Installation
IR Remote Control up to 10-meter
External Connection Terminals
From Full Color Control to Color Pause, and Lighting Memory
White Color & Brightness Adjust
Max. 7.5amp Driving Current
Operate at 12V or 24V DC Voltage


Signal Amplify thru mini_Repeater. More amperes are required? Simply connect to the PWM repeater, model CR90D3-080, which helps to multiply the serial RGB signal up to 3.75A and all attached LED strips then appear to operate synchronously to the Controller.

Tech. Specification

Specification	<i>Order Code</i> CX-145K
Interface	IR, USB, Wall Plate, External
Input Voltage	Typ. 12VDC or 24VDC
Output Voltage	Typ. 12VDC or 24VDC
Current per Output	3.75Amp per R-G-B Output, Total 2 Output
Connection	Screw Terminals
Remote Control Function	Power ON/OFF; 8 Program; 6 Memory; Brightness/Speed Adjust; Chase ON/OFF; Pause; White
Software Program	ColorEdit 1 RGB
OS	Windows 2000, 2003, XP(32bit/64bit), 2008, Vista(32bit/64bit), Windows 7.
Standard Met	RoHS
Warranty	One-year

Software Programming

ColorEdit 1 RGB



BetaOpto Contact

Beta Opto Technology Co., Ltd.

TEL +886 3 658 7662; FAX +886 3 658 9812
 Email contact@betaoptotech.com
 URL betaopto.diytrade.com; www.betaoptotech.com
Design, Manufacturing & Quality in Taiwan

