

Part No.	Package	Wavelength	Data Rate	Reach	Output Power(dBm)	Sens(dBm)	Connector	Voltage
HSP8503-02D	SFP	850nm	155M	2km	-10≤Pout≤-4	≤-25	LC	3.3V
HSP3103-02D	SFP	1310nm	155M	2km	-20≤Pout≤-14	≤-31	LC	3.3V
HSP3103-L2D	SFP	1310nm	155M	20km	-14≤Pout≤-8	≤-32	LC	3.3V
HSP3103-L4D	SFP	1310nm	155M	40km	-5≤Pout≤0	≤-34	LC	3.3V
HSP5503-L8D	SFP	1550nm	155M	80km	-5≤Pout≤0	≤-34	LC	3.3V
HSP5503-12D	SFP	1550nm	155M	120km	0≤Pout≤5	≤-34	LC	3.3V
HSP5503-15D	SFP	1550nm	155M	150km	0≤Pout≤5	≤-37	LC	3.3V
HSP3112-L2D	SFP	1310nm	622M	20km	-15≤Pout≤-8	≤-28	LC	3.3V
HSP3112-L4D	SFP	1310nm	622M	40km	-3≤Pout≤2	≤-28	LC	3.3V
HSP5512-L8D	SFP	1550nm	622M	80km	-2≤Pout≤3	≤-28	LC	3.3V
HSP5512-12D	SFP	1550nm	622M	120km	0≤Pout≤5	≤-31	LC	3.3V
HSP8524-S5D	SFP	850nm	1.25G	500m	-9≤Pout≤-3	≤-18	LC	3.3V
HSP3124-L2D	SFP	1310nm	1.25G	20km	-9≤Pout≤-3	≤-23	LC	3.3V
HSP3124-L4D	SFP	1310nm	1.25G	40km	-5≤Pout≤0	≤-23	LC	3.3V
HSP5524-L8D	SFP	1550nm	1.25G	80km	0≤Pout≤5	≤-23	LC	3.3V
HSP5524-12D	SFP	1550nm	1.25G	120km	0≤Pout≤5	≤-31	LC	3.3V
HSP8548-S3D	SFP	850nm	2.5G	300m	-10≤Pout≤-3	≤-18	LC	3.3V
HSP3148-02D	SFP	1310nm	2.5G	2km	-10≤Pout≤-3	≤-18	LC	3.3V
HSP3148-L2D	SFP	1310nm	2.5G	20km	-5≤Pout≤0	≤-18	LC	3.3V
HSP5548-L4D	SFP	1550nm	2.5G	40km	-2≤Pout≤3	≤-20	LC	3.3V
HSP5548-L8D	SFP	1550nm	2.5G	80km	-2≤Pout≤3	≤-28	LC	3.3V
HSP313G-S5D	SFP	1310nm	3.125G	500m	-9≤Pout≤-3	≤-18	LC	3.3V
HSP313G-L2D	SFP	1310nm	3.125G	20km	-5≤Pout≤0	≤-18	LC	3.3V
HSP854G-S5D	SFP	850nm	4.25G	500m	-9≤Pout≤-3	≤-15	LC	3.3V
HSP314G-L2D	SFP	1310nm	4.25G	20km	-5≤Pout≤0	≤-18	LC	3.3V