











## TS17 Series Righ Angle Illuminated Tact Switches

<b>Pic</b>						
<b>Model</b>	TS17-0000X	TS17-8BE00X	TS17-0023AX1	TS17-0022BX	TS17-0024WX	TS17-0021AX6
<b>Size(mm)</b>	7(L)*7(W)*7(H)	10.5(H)	7.5(φ)*9.0(H)	7.5(φ)*9.0(H)	7.5(L)*7.5(W)*9.0(H)	10(φ)*9.0(H)
<b>Cap Size(mm)</b>	NON	7.5(φ)*6.3(H)	7.5(φ)*2.4(H)	7.5(φ)*2.4(H)	7.5(L)*7.5(W)*2.4(H)	10(φ)*2.4(H)
<b>Terminal Type</b>	Right Angle	Right Angle	Right Angle	Right Angle	Right Angle	Right Angle
<b>Rating</b>	50mA 12VDC	50mA 12VDC	50mA 12VDC	50mA 12VDC	50mA 12VDC	50mA 12VDC
<b>Life</b>	500,000 Cycles Min	500,000 Cycles Min	500,000 Cycles Min	500,000 Cycles Min	500,000 Cycles Min	500,000 Cycles Min
<b>Actuation Force</b>	250±50gf	250±50gf	250±50gf	250±50gf	250±50gf	250±50gf
<b>Total Travel</b>	0.25±0.1mm	0.25±0.1mm	0.25±0.1mm	0.25±0.1mm	0.25±0.1mm	0.25±0.1mm

<b>Pic</b>				
<b>Model</b>	TS17-0027BX1	TS17-00EWX	TS17-00EAX1	TS17-8BEWX
<b>Size(mm)</b>	10(L)*10(W)*9.0(H)	7.5(φ)*12.2(H)	7.5(φ)*12.2(H)	7.5(φ)*16.9(H)
<b>Cap Size(mm)</b>	10(L)*10(W)*2.4(H)	7.5(φ)*6.3(H)	7.5(φ)*6.3(H)	7.5(φ)*6.3(H)
<b>Terminal Type</b>	Right Angle	Right Angle	Right Angle	Right Angle
<b>Rating</b>	50mA 12VDC	50mA 12VDC	50mA 12VDC	50mA 12VDC
<b>Life</b>	500,000 Cycles Min	500,000 Cycles Min	500,000 Cycles Min	500,000 Cycles Min
<b>Actuation Force</b>	250±50gf	250±50gf	250±50gf	250±50gf
<b>Total Travel</b>	0.25±0.1mm	0.25±0.1mm	0.25±0.1mm	0.25±0.1mm